

Wireless panic button

Code: JA-188J

The RC-188J is mainly used as a wireless panic or emergency button. It is designed to be a remote control for setting/unsetting an alarm system or remotely controlling other appliances.



Product description:

It provides **tamper contacts** and **monitors the voltage** of its battery.

The system **reaction to button activation is optional**. The basic reaction is a panic alarm or setting/unsetting the system (selectable).

Other reactions can be chosen in control panel service mode.

Technical information:

Voltage	Lithium battery type CR14250 (1/2 AA) 3.6V/1.2 Ah Please note: Battery is not included
Typical battery lifetime	approximately 3 years (20 daily activations)
Communication band	868.1 MHz, Jablotron protocol
Communication range	approx. 300 metres (open area)
Dimensions, weight	80 x 80 x 29 mm, 60 g
Operational environment according to	EN 50131-1 class II. Indoor general
Operational temperature range	-10 °C to + 40 °C
Complies with EN 50131-1, EN 50131-5-3, EN 50134-2	grade 2
Complies with	ETSI EN 300220, EN 50130-4, EN 55022, EN 60950-1
Can be operated according to	ERC REC 70-03