

## Wireless remote control

Code: JA-182J

The JA-182J remote control is designed to remotely arm/disarm the system, activate panic alarms and control equipment . The key fob has a built-in convenient "child lock".



### Product description:

The "Child Lock" feature prevents the accidental activation of the unit. Pressing 2 buttons activates a panic alarm.

### Technical information:

<b>Power</b>	lithium battery type CR 2032 (3.0 V) Please note: Battery is not included (Source type C according to EN 50131-6)
<b>Typical battery life</b>	about 4 years (5 activations/day)
<b>Communication band</b>	868.1 MHz
<b>Communication range</b>	about 30 meters (open area)
<b>Environment according to EN 50131-1</b>	II. general indoor
<b>Operating temperature range</b>	-10 °C to +40 °C
<b>Classification according to EN 50131-1</b>	Grade 2
<b>Can be operated to</b>	ERC REC 70-03
<b>Meets</b>	ETSI EN 300220, EN 50130-4, EN 55022, EN 60950-1